

IR, MIXER

4.3 to 8.5 GHz

IR4090MF2-126

PRODUCT FEATURE

- †Broadband Frequency Application
- †Excellent Conversion Loss
- †High Isolation
- †Frequency Converter Application

ABSOLUTE MAXIMUM RATING:

Operating Temperature:	-54°C to +125°C
Storage Temperature:	-65°C to +150°C
Peak Input Power for any Single Port:	+23 dBm Peak
Peak Input Power for all Port:	+26 dBm Peak
Peak Input Current @ 25°C:	100 mA

Parameters	SPECIFICATION @ 25°C				
	FREQ. (GHz)	MIN (dB)	TYPICAL (dB)	MAX (dB)	CONDITONS
CONVERSION LOSS					
RF OUTPUT	5.2 to 8.5				
LO INPUT	4.3 to 7.6				
IF INPUT	0.9 ± .02		7.0	8.0	
VSWR	LO & IF RF		2.0		
IN BAND SPURIOUS					
2LO X -4IF			-60 dBc		
2LO X -3IF			-60 dBc		
INPUT IP ₃		20 dB			
1 dB Compression Point			+4 dBm		
LO Drive			+10 dBm		
IMAGE REJECTION		16 dB	18 dB		
OPERATING TEMP RANGE(°C)		-40		+85	

NOTES:

1. Typical values are measured at +25°C and are not guaranteed

IR, MIXER

4.3 to 8.5 GHz

IR4090MF2-126